



KENYON "T" LINE TRANSFORMERS

MODULATION TRANSFORMERS

Type No.	Primary Ohms	Max. Audio Level	Ohms	Secondary M.A.	Ohms	M.A.	Ohms	M.A.	Case No.	List Price
T-451	10,000	10 watts	5,000	100	3,000	100			2A	\$4.50
T-452	15,000	5 watts	5,000	50	3,000	50			1A	3.75
T-453	5,000	20 watts	5,000	130	3,000	130			4A	7.75
T-454	10,000 or 6,000	30 watts	8,000	75	6,000	100	4,000	140	4A	7.75
T-455	10,000	60 watts	9,000	130	7,000	150	5,000	180	5A	12.25
T-456	2,000	40 watts	9,000	100	7,000	125	5,000	150	5A	12.25
T-457	5,000 or 3,000	60 watts	7,000	120	5,000	160	3,000	220	5A	12.25
T-458	10,000	80 watts	9,000	130	7,000	150	5,000	180	6A	12.25
T-459	3,800	60 watts	7,000	200	5,000	250	2,500	300	5A	11.75
T-460	12,000	100 watts	10,000	150	8,000	175	6,000	200	6A	13.75
T-461	16,000	140 watts	10,000	175	7,000	200	5,000	240	6A	14.75
T-462	7,000	140 watts	8,000	200	6,000	250	4,000	300	6A	14.75
T-463	11,000	500 watts	6,000	400	4,000	500	3,000	570	8A	42.50
T-464	12,000	300 watts	8,000	250	6,000	300	4,000	370	7A	26.75
T-465	(Replaced by T-479)									
T-466	8,400	110 watts	8,000	160	5,000	200	3,000	270	6A	14.75
T-467	7,200	200 watts	6,500	240	4,500	280	3,000	350	7A	24.00
T-468	16,000	400 watts	8,000	300	5,000	375	3,000	500	8A	42.50
T-469	12,000	70 watts	10,000	120	7,000	140	4,500	180	5A	12.25
T-470	(Replaced by T-480)									
T-477	6,700 or 4,700	80 watts	10,000	130	7,000	160	4,500	200	5½A	12.25
T-478	16,000	225 watts	7,000	270	5,000	320	3,500	400	7A	26.50
T-479	9,000 or 6,700	300 watts	8,000	250	6,000	300	4,000	370	7A	27.00
T-480	9,000 or 6,700	500 watts	8,000	350	6,000	400	4,000	500	8A	42.50

KEN-O-TAP MODULATION TRANSFORMERS

KEN-O-TAP Transformers never grow obsolete! Ideal for amateurs who wish to keep up to date with new tube combinations. Will match any Class B tube or tubes to any Class C load.

Type No.	Audio Output Primary	Class "C" Secondary	Primary Range	Secondary Range	Case No.	List Price
T-489	15 watts	30 watts	2000 - 20000	200 - 20000	3A	5.00
T-493	40 watts	80 watts	2000 - 20000	200 - 20000	4A	7.25
T-494	75 watts	150 watts	2000 - 20000	200 - 20000	5A	10.75
T-495	125 watts	250 watts	500 - 18000	200 - 19000	7A	24.00
T-496	300 watts	600 watts	500 - 18000	200 - 19000	8A	36.50

CATH-O-DRIVE TRANSFORMERS

KENYON again leads the way with a new series of four CATH-O-DRIVE modulation transformers, designed to be used with the new cathode system of modulation. This new method employs a small modulation transformer in the cathode circuit of the class "C" stage delivering audio power equal to a small percentage of the class "C" input. Class "C" constants are the same as for plate modulation. Here is a real economical solution for inexpensive modulation and a method which will give most excellent results.

A complete sheet showing impedances for various types of modulation tubes will be mailed upon request without charge.

Type	D. C.	Audio Tubes	Case No.	List Price
T-471	200 MA	SINGLE 6F6	2A	4.50
T-472	300 MA	PP 6V6's or 2A3's	3A	5.50
T-473	450 MA	PP 6L6's AB or AB2	4A	6.75
*T-474	500 MA	UNIVERSAL	6A	13.25

*Handles 120 Watts Audio.

Secondary Impedances range from 40 to 3000 ohms in convenient taps.

PLATE TRANSFORMERS FOR STANDARD AMATEUR DUTY

Type No.	Secondary Voltage	D.C. Volts	D.C. M.A.	Case No.	List Price
T-668	1000/750-0-750/1000	500/750	300	5½A	10.75
T-669	1460/1180-0-1180/1460	1000/1250	300	7A	17.50
T-670	2360/2080/1760-0-1760/2080/2360	1500/1750/2000	300	8A	24.00
T-671	1460/1180-0-1180/1460	1000/1250	500	8A	24.00
T-672	1760/1460/1250-0-1250/1460/1760	1000/1250/1500	300	8A	21.75

Fully Poured - Vacuum Varnish Impregnated