



No.	Name	Color	Destination
1	AT1	YEL	SW (M)
2	AT2	BLU	SW (M)
3	MKR	GRY	PLL unit (6)
4	PL5	GRN	PLL unit (2)
5	AT4	BLU	PLL unit (1)
6	ARO	GRY	Digital unit (1)
7	RB3	YEL	Digital unit (1)
8	RB2	WHT/GRN	Digital unit (1)
9	RB1	WHT/VIO	Digital unit (1)
10	RB0	WHT/BLU	Digital unit (1)
11	VSR	ORG	LPF unit (3)
12	G	GRY	LPF unit (3)
13	VSF	RED	LPF unit (1)
14	TV	GRN	LPF unit (1)
15	BST	ORG	LPF unit (1)
16	THP	YEL	LPF unit (1)
17	18	RED	Final unit (1)

No.	Name	Color	Destination
1	FCB	BRN	PLL unit (1)
2	VCH	RED	PLL unit (3)
3	VCM	ORG	PLL unit (3)
4	VCL	YEL	PLL unit (1)
5	FCV	RED	PLL unit (1)
6	FCG	RED	PLL unit (1)
7	NA	GRY	Signal unit (2)
8	NBB	GRY	Signal unit (2)
9	NG1	GRY	Signal unit (2)
10	ISW	BLU	AT unit (2)
11	ICA	BRN	Power supply unit (6)
12	ICB	WHT	Power supply unit (6)
13	NG2	YEL	Signal unit (2)
14	FSK	WHT	SW (A) MODE SW10-1
15	PRM	BRN	SW (E) METER SW
16	PRS	ORG	SW (C)
17	PRL	YEL	SW (D) VR1-2

No.	Name	Color	Destination
1	MV2	BLU	SW (C) PRO SW S8
2	G	GRY	SW (C)
3	CWN	RED	SW (C)
4	AMN	ORG	SW (C)
5	AMW	YEL	SW (A)
6	VF2	GRN	SW (A)
7	G	GRY	PLL unit (3)
8	AFS	RED	PLL unit (3)
9	DLY	GRY	PLL unit (3)
10	V12	VIO	SW (K)
11	ANV	BRN	SW (K)
12	VX0	WHT	SW (K)
13	VX2	RED	SW (K)
14	VX1	BLU	SW (K)
15	MV1	RED	SW (D) VR1-1
16	SSA	BRN	SW (A)
17	G	GRY	SW (A)
18	MCL	BLU	SW (J)

No.	Name	Color	Destination
1	G	GRY	LINE IN jack
2	MCH	GRY	LINE IN jack
3	LINE	BLU	LINE IN jack
4	AGO	VIO	SW (E)
5	RFG	YEL	SW (F)
6	NTH4	ORG	SW (F)
7	NAM	WHT	SW (E)
8	AGS	GRY	SW (E)
9	G	GRY	IF OUT terminal
10	IFO	GRY	IF OUT terminal
11	AM	VIO	SW (A)
12	CW	GRY	SW (A)
13	CWP	WHT	SW (A)
14	AP5	BRN	SW (N)
15	AP4	RED	SW (A)
16	AP3	GRN	SW (A)
17	AP1	YEL	SW (A)
18	M	BLU	METER SW (E)
19	WHT/BRN	WHT/BRN	METER SW (E)
20	AP0	WHT/RED	METER SW (N)

No.	Name	Color	Destination
1	SP1	RED	LINE OUT terminal
2	G	GRY	LINE OUT terminal
3	SP2	ORG	EXT. SP jack
4	STK	VIO	KEY jack
5	KEY	GRY	KEY jack
6	AV1	RED	SW (F)
7	SP1	ORG	PHONE jack
8	G	GRY	PHONE jack
9	SP2	YEL	PHONE jack
10	NB1	GRN	SW (M) NB2 SW
11	NB2	BLU	SW (F)
12	AV2	BLU	SW (F)
13	G	GRY	PLL unit (8)
14	NG2	YEL	Signal unit (18)

No.	Name	Color	Destination
1	BLK	GRN	Digital unit (2)
2	V51	GRN	Digital unit (2)
3	TR	VIO	Digital unit (2)
4	UL	GRY	Digital unit (2)
5	C	WHT	Digital unit (2)
6	DA	BRN	Digital unit (2)
7	NBB	GRY	Signal unit (7)
8	NG1	GRY	Signal unit (7)
9	RAL	WHT	REMOTE socket
10	XAL	BRN	X. VTER socket
11	RVL	VIO	REMOTE socket
12	RV	ORG	SW (H)
13	ATV	YEL	SW (H)
14	XVL	GRN	X. VTER socket
15	XVR	BLU	X. VTER socket
16	G	GRY	PLL unit (8)
17	NG2	YEL	Signal unit (18)
18	28A	YEL	R1 - R3270 2W

No.	Name	Color	Destination
1	V52	YEL	SW (I) VOX/MAN SW S2
2	V51	GRN	SW (I) VOX/MAN SW S2
3	FBK	BLU	SW (I) FULL/SEMI SW S3
4	SS	VIO	SW (C) STBY SW S6
5	NTF	WHT	SW (A)
6	TC	GRY	SW (A)
7	LSB	VIO	SW (A)
8	USB	GRN	SW (A)
9	VF1	BLU	SW (A) MODE SW10-5
10	CV	YEL	SW (D) VR2-2
11	M51	ORG	SW (I) MONI SW S4
12	M52	BRN	SW (I) MONI SW S4
13	TUN	BRN	SW (A) MODE SW10-1
14	RV	GRN	SW (A) MODE SW10-1
15	AM	ORG	SW (A) MODE SW10-1
16	ALM	YEL	SW (E)
17	18	RED	SW (A) MODE SW10-3
18	PWR	BLU	SW (E)
19	VIO	VIO	SW (A) MODE SW10-2
20	ICM	GRN	SW (E)
21	VCM	GRN	SW (E)
22	SWR	BRN/WHT	SW (E)

Terminal name	Color	Destination
VCOF	BLK	PLL unit "VCO"
VCOF	GRY	RF unit "VCOF"
RF (FRO)	GRY	RF unit "RFO"
RAT	GRY	X. VTER jack SW
BLK	GRY	PLL unit "HET"
RIF	GRY	RF unit "RIF"
XVT	GRY	X. VTER jack
DRV	GRY	Final unit "IN"
RED	RED	RED
ORG	ORG	ORANGE
VIO	VIO	VIOLETT
GRY	GRY	GRAY
WHT	WHT	WHITE
YEL	YEL	YELLOW
BLU	BLU	BLUE
BRN	BRN	BROWN
GRN	GRN	GREEN
BLK	BLK	BLACK